



TYPE	NON-MAINTAINED NÃO PERMANENTE	MAINTAINED PERMANENTE
DESCRIPTION	Bulkhead for emergency lighting	Bloco autónomo de iluminação de segurança
PRODUCT CODE	6012-047	6012-046
INPUT VOLTAGE	230 VAC	230 VAC
FREQUENCY	50-60Hz	50-60Hz
AC POWER	5W	5W
DC POWER	1,3W	3,4W
RATED LUMINOUS FLUX	90 lm	120 lm
REMOTE CONTROL VOLTAGE	5-24VDC	5-24VDC
BATTERY TYPE	Ni-Cd 4,8V 500mAh	Ni-Cd 4,8V 500mAh
DISCHARGING TIME	1 H	1 H
CHARGING TIME	> 24H	> 24H
BATTERY LIFETIME	500 cycles	500 cycles
OPERATING TEMPERATURE	-10°C > 50°C	-10°C > 50°C
SIZE	257x115x53 mm	257x115x53 mm
PVP (EUROS)	52,60	52,60

MAINTAINED

- 24h / 7 days a week on
- Power: 5W AC when the electrical facility is running and the battery is fully charged. 8W AC when the electrical installation is running and the battery is charging. 3,4W DC in emergency situations. The energy consumed comes from the battery.

NON-MAINTAINED

- Remain off when the electrical facility is OK. Turns on only when emergency situations are detected.
- Power: 1.3W DC in emergency situations.

PERMANENTE

- 24h / 7 dias por semana ligado
- Potência: 5W AC quando a instalação elétrica está a funcionar e a bateria está totalmente carregada. 8W AC quando a instalação elétrica está a funcionar e a bateria está em carga. 3,4W DC quando se detetam situações de emergência. A energia consumida é proveniente da bateria.

NÃO PERMANENTE

- Mantém-se desligado quando a instalação elétrica está em boas condições de funcionamento. Liga-se somente quando se detetam situações de emergência
- Potência: 1,3W DC quando se detetam situações de emergência.



Compatible with any remote controls of leading brands with 5-24VDC output voltage. Possibility of enabling the emergency function by a single remote control.

Compatível com qualquer telecomando das principais marcas com uma tensão de saída de 5-24VDC. Possibilidade de activar a função de emergência com um só comando.

